Specification sheet



QSK60-G11

Fuel Optimized



Description

The QSK60 is a V 16 cylinder engine with a 60 litre displacement. This Quantum series utilizes sophisticated electronics and premium engineering to provide outstanding performance levels, reliability and versatility for Standby, Prime and Continuous Power applications.



This equipment has been built to comply with CE certification requirement subject to EU RoHS exclusion per EU 2011/65.



This engine has been designed in facilities certified to ISO9001 and manufactured in facilities certified to ISO9001 or ISO9002.

Features

High pressure fuel pump, Modular Common Rail fuel System (MCRS) and state of the art integrated electronic control system provide superior performance, efficiency and diagnostics. The electronic fuel pumps deliver up to 1600 bar injection pressure and eliminate mechanical linkage adjustments. The new MCRS utilizes an electric priming pump which is integrated with the off-engine stage-1 fuel filter head and is controlled and powered by the engine ECM. The stage-2 fuel filters are mounted on-engine.

CTT (Cummins Turbo Technologies)
HX82/HX83 turbocharging utilizes exhaust
energy with greater efficiency for improved
emissions and fuel consumption.

Low Temperature After-cooling - Two-pump Two-loop (2P2L)

Ferrous Cast Ductile Iron (FCD) Pistons -High strength design delivers superior durability.

G-Drive Integrated Design - Each component has been specifically developed and rigorously tested for G-Drive products, ensuring high performance, durability and reliability.

Service and Support - G-Drive products are backed by an uncompromising level of technical support and after sales service, delivered through a world class service network.

Coolpac Integrated Design - Products are supplied complete with cooling package and air cleaner kit for a complete power package. Each component has been has been specifically developed and rigorously tested for G-Drive products, ensuring high performance, durability and reliability

1500 rpm (50 Hz ratings)

Gross engine output Standby Prime Base		Ne	Net engine output			Typical generator set output					
		Standby	Prime	Base	Standby (ESP)		Prime (PRP)		Base	Base (COP)	
	kWm/BHP		kWm/BHP		kWe	kVA	kWe	kVA	kWe	kVA	
1955/2620	1730/2319	1395/1870	1901/2549	1695/2273	1360/1823	1800	2250	1600	2000	1306	1632

1800 rpm (60 Hz ratings)

Gross engine output		Net	engine out	put	Typical generator set output		put				
Standby Prime Base		Standby	Prime	Base	Standby (ESP)		Prime (PRP)		Base (COP)		
kWm/BHP			kWm/BHP		kWe	kVA	kWe	kVA	kWe	kVA	
-	-	-	-	-	-	-	-	-	-	-	-

General engine data

Туре	4 cycle, turbocharged, After-cooled
Bore mm	159
Stroke mm	190
Displacement litre	60.2
Cylinder block	Cast iron, 16 cylinder
Battery charging alternator	55 amps
Starting voltage	24 volt, negative ground
Fuel system	Direct Injection Cummins MCRS
Fuel filter	Spin-on fuel filters with water separator
Lube oil filter type(s)	Spin-on full flow filter
Lube oil capacity (I)	280
Flywheel dimensions	SAE 0

Coolpac performance data

Cooling system design	2 pump - 2 loop	2 pump - 2 loop		
Coolant ratio	50% ethylene glycol; 50%	water		
Coolant capacity (I)	535 (40C Rad.)	603 (50C Rad.)		
Limiting ambient temp.** (°C)	43	48		
Fan power (kWm)	46	39		
Cooling system air flow (m³/s)**	35	31		
Air cleaner type	Dry replaceable element w	Dry replaceable element with restriction indicator		

^{** @ 13} mm H₂0

Fuel consumption 1500 (50 Hz)

%	kWm	ВНР	L/ph	g/kWh			
Standby Power							
100	1955	2620	465	122.6			
Prime Power							
100	1730	2319	403	106.4			
75	1297	1739	304	80.4			
50	865	1160	207	54.7			
25	432	580	119	31.3			
Continuous Power							
100	1395	1870	327	86.2			

Fuel consumption 1800 (60 Hz)

%	kWm	ВНР	L/ph	g/kWh	
Standby P	ower				
100	-	-	-	-	
Prime Pow	/er				
100	-	-	-	-	
75	-	=	=	-	
50	-	-	-	-	
25	-	-	-	-	
Continuous Power					
100	-	-	-	-	

Weights and dimensions

Length mm	Width mm	Height mm	Weight (dry) kg	_
4893	2468	2943	10295	(40C Rad.)
5176	2468	3868	11010	(50C Rad.)

Ratings definitions

Emergency Standby Power (ESP):	Limited-Time Running Power (LTP):	Prime Power (PRP):	Base Load (Continuous) Power (COP):
Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. Emergency Standby Power (ESP) is in accordance with ISO 8528. Fuel Stop power in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.	Applicable for supplying power to a constant electrical load for limited hours. Limited-Time Running Power (LTP) is in accordance with ISO 8528.	Applicable for supplying power to varying electrical load for unlimited hours. Prime Power (PRP) is in accordance with ISO 8528. Ten percent overload capability is available in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.	Applicable for supplying power continuously to a constant electrical load for unlimited hours. Continuous Power (COP) in accordance with ISO 8528, ISO 3046, AS 2789, DIN6271 and BS 5514.

For more information contact your local Cummins distributor or visit cummins.com

